

adhoc[®] DMX RX

Art nr: AH-DMX-RX

Adhoc Wireless DMX receiver

This unit is perfect when you need reliable wireless DMX in areas with limited physical access.

- 2.4Ghz Lumenradio CRMX receiver
- 1 DMX universe up to 512 channels
- Link range up to 1000 meters
- Compatible with CRMX transmitter
- Status LED indicators

A large number of Adhoc DMX RX can be linked to one Lumenradio CRMX transmitter.

Embedded power supply. Just plug and play!



TECHNICAL SPECIFICATION

Operating voltage	200–265V AC
Ambient temperature (operating)	10–35 °C
Range	0–1000m line-of-sight
Latency	Fixed 5 ms end-to-end
Antenna type	Chip antenna
Operating frequency	2402–2480 MHz
Receiver sensitivity	0.1% BER: Typ. -93dBm
DMX frame size	0–512
DMX frame rate	0.8–830 fps
Dimension (LxWxH)	139.8 x 44.9 x 26 mm
Protection class	IP20

